

36V Surge Voltage High Side Over-Voltage Protector with 500V 7V TVS in DFN3x3

DESCRIPTION

ETA7016 is a 36V surge voltage over voltage protector (OVP) integrated with a 500V TVS diode, which has a very low 33mohm on resistance. It can be used as an OVP device or a high voltage switch at power input port.

ETA7016 consists of a charge pump, a configurable power MOSFET, a voltage reference, a gate driver, some logics, protection modules and a 500V TVS diode. ETA7016 can react to an input surge very fast and shut off the switch in less than D.lus and stand the voltage spike as high as 36V.

ETA7016 is in DFN3x3-12 package.

FEATURES

- Operation Voltage up to 7V
- 36V surge voltage
- 33mohm on resistance
- Input OVP with 0.1us reaction time
- 500V TVS
- Protection voltage programmable by Vfb=1.26V
- SCP and OTP
- Enable pin available for switch on and off

APPLICATIONS

- All electronic devices with input DC power plug
- Cellphone
- E-Cigarette
- Car Camera



TYPICAL APPLICATION

www.etasolution.com



PIN CONFIGURATION



ABSOLUTE MAXIMUM RATINGS

(Note: Exceeding these limits may damage the device. Exposure to absolute maximum rating conditions for long periods may affect device reliability.)

FB Voltage		0.	3V to 6V	
IN, DUT. EN Voltage (internally clamped)		–0.3V to 7V		
Operating Temperature Range		40°C to 85°C		
Storage Temperature Range		55°C	to 150°C	
Thermal Resistance	θJC	θ_{JA}		
DFN3x3-12	10	30	°C/W	
Lead Temperature (Soldering,	10ssec)		260°C	
ESD HBM (Human Body Mode)			2KV	
ESD MM (Machine Mode)			200V	

ELECTRICAL CHACRACTERISTICS

$(V_{IN} = 5V, unless otherwise specific$	ed. Typical values are at TA = 25°C.)				
PARAMETER	CONDITIONS	MIN	ТҮР	MAX	UNITS
IN Range		3.35		7	٧
UVLO	Hys=400mV		3.35		٧
OVP	Default OVP=6.1V when FB short to GND	5.9	6.1	6.3	V
OVP FB	Vin=5V	1.21	1.26	1.31	۷
OVP Range		3.5		7	V
Ron	Vin=5V, lout=2A		33		mΩ
lout_max	The maximum output peak current		4	NC	Α
Vsurge	Surge Voltage protected by internal TVS		500	N.D	٧
lq	Standby current, Vin < 7V voltage, EN=high		160		uА
lsd	Shutdawn current, Vin=5V		30		uА
Thermal Shutdown	Rising, Hys=50°C		135		Jo

PIN DESCRIPTION

PIN #	NAME	DESCRIPTION
1, 2, 9, 11, 12	IN	Connected to the power input port of a system. Bypass with a luF capacitor from this pin to GND.
3, 4, 10	GND	Ground
5	EN	Enable pin, pull high to turn on the chip and pull low to shut down the chip.
6	FB	OVP feedback input pin. A resistor divider from IN to AGND thru this pin. VFB=1.26V. When FB floating, default DVP=6.1V.
7, 8	OUT	OUTPUT pin, Bypass with a luF capacitor from this pin to ground.

www.etasolution.com





Over Voltage Protection Waveforms (with Cf=47pF, Cout=0.luF, externally setting Vovp=6.IV)

450V Surge Voltage OVP Waveforms (with Cin=luF, Cout=0.luF, FB short to GND, Vovp=6.IV)



Enable ON and OFF Waveforms



ETA7016



TYPICAL CHARACTERISTICS

(Typical values are at TA=25°C unless otherwise specified.)



APPLICATION NOTE

Default OVP level when FB Float

One can short FB to GND if only want to set over voltage level at 6.1V.

Setting DVP level when connecting resistor divider on FB pin $Vovp = 1.26 \times \frac{R1+R2}{R2}$ (V) where Vovp has to be within the range from 3.5 to 7V.

PCB GUIDE

A PCB guide is shown on the right hand, with only 2 small capacitors are needed for ETA7016, if OVP is set internally and EN is pulled high to input.

Please be aware of the three exposed pads are better be connected to IN (the exposed pad connected to pin 9) and to GND (the exposed pad connected to pin 3 and 10, and the exposed pad connected to pin 4).





MAX

0.8 0.05

0.25

1.8

0.65 0.75 1.275 1.225 1.125

PACKAGE OUTLINE

Package: DFN3x3-12



BOTTOM VIEW